

### Uzaktan Erişim için mOTP kullanın

One-time password (OTP), yalnızca bir oturum açma için geçerli olan bir şifredir, password-based authentication tekrarlama saldırılarına karşı koruyabilir. Router'in Remote Access için (WAN arayüzünden oturum açın), OTP'yi kullanabilir ve Router'e ve Local ağınıza bir güvenlik katmanı ekleyebilirsiniz. Bu, bir kerelik parola üreten bir cihaz, genellikle bir cep telefonu gerektirir.

1. Akıllı telefonunuza bir mOTP APP (örneğin, mOTP - mobilOneTimePasswords) yükleyin.
2. Yeni bir profil oluşturun, 4 haneli PIN kodunu ve 16 haneli Secret tanımlayın, ardından Save'e tıklayın.



The screenshot shows the 'MOTP Profile' configuration screen. At the top, there are 'Back' and 'Delete' buttons. The title is 'MOTP Profile' with an information icon. Below the title, there are three input fields: 'Name' with the value 'Testing', 'Pin' with the value '1234', and 'Secret' with the value '1234567887654321'. Below these fields is an 'Advanced' section with a toggle switch currently set to 'Off'. At the bottom, there is a 'Save' button with a checkmark icon.

3. Router üzerinde, **System Maintenance >> Administrator Password Setup** sayfasına gidin, Step 2'de tanımlanan PIN Code ve aynı Secret'i girin.

#### System Maintenance >> Administrator Password Setup

##### Administrator Password

Old Password	<input type="text"/>	
New Password	<input type="text"/>	(Max. 23 characters allowed)
Confirm Password	<input type="text"/>	(Max. 23 characters allowed)
<input checked="" type="checkbox"/> Use only advanced authentication method for Admin "WAN" login		
<input checked="" type="radio"/> Mobile one-Time Passwords(mOTP)		
PIN Code	<input type="text" value="*****"/>	Secret <input type="text" value="*****"/>
<input type="radio"/> 2-Step Authentication		
Send Auth code via		
<input type="checkbox"/> SMS Profile	1 - Test	To : +886
<input checked="" type="checkbox"/> Mail Profile	1 - Gmail	@draytek.com

##### Note:

Password can contain only a-z A-Z 0-9 , ; : . " < > \* + = | ? @ # ^ ! ( )

4. Router'e giriş yaparken, önce mobil APP'de bir defalık bir şifre oluşturmanız gerekir. Uygulamaya aynı PIN Code girin ve ardından Generate butonuna tıklayın.

MOTP

One time password

Profile: Testt

Pin: pin - 4 cifre

dda5f5

Remaining (s): 163

Generate

5. Router'e internetten bir dakikalık bir süre için geçerli olan bu bir seferlik şifre ile giriş yapabilirsiniz. Parolanın süresinin dolması durumunda şifreyi tekrar oluşturmanız gerekecektir.



The image shows the login interface for a DrayTek Vigor2860 Series router. The page has a red header with the DrayTek logo on the left and 'Vigor2860 Series' on the right. Below the header is a black bar with the word 'Login' in white. The main content area is white and contains the text 'Router Login' centered. There are two input fields: 'Username' and 'Password'. Below the input fields is a grey 'Login' button. At the bottom of the page, there is a copyright notice: 'Copyright © 2000-2017 DrayTek Corp. All Rights Reserved.'

**DrayTek** **Vigor2860 Series**

**Login**

**Router Login**

**Username**

**Password**

**Login**

Copyright © 2000-2017 DrayTek Corp. All Rights Reserved.